

# SMART CHARGER

Model: SCharger-7KS-S0/SCharger-22KT-S0



Single-Phase

**7.4** kW/32 A  
SCharger-7KS-S0

Three-Phase

**22** kW/32 A  
SCharger-22KT-S0

\*Available in specific regions only



#### PV Power

Power Your Car with Solar  
Make EV Even Greener



#### Dynamic Charging Power

Automatic Detection and  
Adjustment  
No Worry about Overload



#### 3 Ways of Authentication

Authentication through  
Bluetooth, RFID and APP



#### 3-Step Installation

Fast Installation in 15 Min  
Wiring-free Maintenance

# ● SCharger-7KS-S0/SCharger-22KT-S0 Technical Specifications

| Technical Specification                            | SCharger-7KS-S0   | SCharger-22KT-S0                             |
|--|---|--|
| Inputs and Outputs                                 |   |  |
| Charge power (configurable)                        | 1.4 kW to 7.4 kW  | 1.4 kW <sup>1</sup> to 22 kW                 |
| Nominal voltage                                    | 230 V ± 20% (1-phase)   | 400 V ± 20% (3-phase)                        |
| Nominal current (configurable)                     | 6–32 A (1-phase)  | 6–32 A (3-phase or 1-phase)                  |
| Nominal frequency                                  | 50 Hz/60 Hz ± 1 Hz  |  |
| Vehicle connection                                 | Type 2 socket   |  |
| Cable cross-sectional area                         | Up to 10 mm <sup>2</sup>  |  |
| Network types                                      | TN, TT, IT  | TN, TT                                       |
| User Interface & Communications                    |   |  |
| Protocol   | Modbus TCP, OCPP 1.6 <sup>2</sup>   |  |
| Communication                                      | Wi-Fi/Ethernet  |  |
| Charger status information                         | WRGB LED and app  |  |
| Authentication                                     | RFID (ISO-14443-A), app, Bluetooth  |  |
| Remote control & monitoring                        | App   |  |
| Working mode                                       | Normal Charge<br>Scheduled Charge<br>PV Power Preferred<br>Next Trip <sup>3</sup>                     |  |
| Protection   |   |  |
| Cable protection                                   | Cable E-Lock via app  |  |
| Residual current protection (RCD)                  | Type A (30 mA) + DC 6 mA integrated   |  |
| Fire class   | UL94  |  |
| Overcurrent protection                             | IEC 61851-1   |  |
| Over-temperature protection                        | Yes   |  |
| Surge protection                                   | CAT II  |  |
| General Specification                              |   |  |
| Operating temperature range                        | -35°C to +45°C  | -35°C to +50°C @ 16A<br>-35°C to +40°C @ 32A |
| Application environment                            | Outdoor/Indoor  |  |
| Storage temperature                                | -40°C to +70°C  |  |
| Relative humidity                                  | 5%–95% RH   |  |
| Altitude   | ≤ 2000 m (Derated between 2000–4000 m)  |  |
| Dimensions (H x W x D)                             | 335 mm x 180 mm x 145 mm  |  |
| Weight   | 3 kg  | 3.1 kg                                       |
| Installation mode                                  | Wall-mounted  |  |
| IP rating  | IP54  |  |
| Impact protection level                            | IK10  |  |
| Standby self-consumption                           | < 6 W   |  |
| Standards Compliance (More Available Upon Request) |   |  |
| Safety & health                                    | EN IEC 61851-1 2019, EN 62311 2008, EN IEC 62311 2020, EN 50665 2017, EN 50364 2018                   |  |
| EMC  | EN IEC 61851-21-2 2021, EN 301 489-1 V2.2.3 2019, EN 301 489-3 V2.1.1 2019, EN 301 489-17 V3.2.4 2020 |  |
| Radio  | ETSI EN 300 328 V2.2.2, ETSI EN300 330 V2.1.1   |  |
| RoHS   | EN IEC 63000:2018   |  |
| Others   |   |  |
| Accessories  | RFID Card * 2   |  |

\*1 1.4 kW for 1-phase charging and 4. 2 kW for 3-phase charging

\*2 Only residential scenario is supported, commercial billing capability of OCPP is not supported.

\*3 Next Trip mode is only available with EMMA-A02.

Disclaimer: The preceding values are measured by an internal laboratory of Huawei in a specific environment. The actual values may vary with products, software versions, usage conditions, and environmental factors.